

I'm not a bot































Samsung SDR-5102N2T Security DVR without WiFi Adapter Samsung SDR-5102N2T is a DVR that is suitable for both home and businesses, compatible for use with computers and smart phones to let you view wherever you are in the world at any time with the remote viewing on iPolis mobile app or Internet Explorer on your PC, working as part of the Samsung SDS-P5102 16 channel security. As an open box but brand new unit, it lacks the original packaging and the WiFi adapter but has all the related accessories. This great quality 16 channel DVR uses H.264 compression method for recording, 30 frames per second at 960H real-time monitoring (maximum resolution of 960 x 480), comes with very large 2TB storage, USB 2.0, HDMI and VGA outputs and includes 16 BNC ports to connect up to 16 cameras and 16/4 Alarm In/Out. Black Samsung DVR looks sleek and modern, weighs 14 pounds and the package measures 12 x 14 x 18 inches. It is easy to set up and use- ready to go straight out of the box with its easy to manage touch control panel, you can download iPolis mobile on both your Android and iPhone devices and you will also get an integrated display, support for multiple languages, PTZ support, Coaxitron support, email notifications. You have the 2TB internal storage and you can't add more internal storage but you should be able to hook up an external storage device. Samsung 16 channel Security System is easily customisable so you benefit from an advanced monitoring system with great notification options and you can respond immediately. When one of the cameras is covered, redirected or damaged or motion is detected you will get live video from your Android or iPhone smartphone or tablets on the iPolis app. Samsung SDS-P5102 includes 10 weather-proof cameras and you can have 6 more as being a 16 channel surveillance system. Using Samsung's Smart Viewer Central Management software you can oversee several systems in different parts of the world at once on your single display- monitor or screen. With the Privacy Masking function you can exclude parts that you don't wish to view by blocking as many as four areas of each camera's viewing field. Samsung WiFi adapter (SEA-W01ACN) is not included with this DVR but with it you will not need network cable connection and you can put the DVR anywhere suitable in your home or office as long as within the wireless range. And for a complete all-in-one unit and other related products please check the Amazon.com product page that you will reach through the links here. \*Samsung is a global brand for a variety of electronics, especially HDTV's and mobile phone and they also make awesome security and surveillance systems you can rely on and at reasonable prices. Click here for a closer look on Amazon Quick Start Guide KIT MODEL SDS-P3042 / P4042 / P4082/ P5082 / P5102 / P5122 DVR MODEL SDR-3102 / 4102 / 5102 SAMSUNG ALL-IN-ONE SECURITY SYSTEM english Thank you for purchasing a Samsung DVR Security System. Follow the simple steps in this guide to set up and start using your new system. If you have any questions or need help installing your new product please contact our free technical support. Telephone: 1-877-349-3149 9am - 9pm EST, Monday - Friday Internet:  8ch DVR Rear IN1 VIDEO IN IN3 AUDIO IN2 IN LAN VGA IN4 AUDIO eSATA OUT HDMI USB RS485 DC12V 4 3 5 2 16ch DVR LAN Rear VIDEO IN IN1 IN2 IN3 AUDIO IN4 IN VGA AUDIO OUT HDMI eSATA RS485 LAN USB DC 12 V 3 4 5 2  connecting the DVR to Live monitoring Front POWER REC NETWORK 1 Connect a mouse 2 . EnglishRear CH1 VIDEO IN CH2 CH4 IN1 IN2 IN3 IN4 AUDIO IN eSATA VGA HDMI AUDIO OUT USB RS485 English CH3 LAN 3 Connect the DC adaptors (Camera) DC 12 V 2 Connect an BNC camera eSATA CH1 CH2 CH3 CH4 CH9 CH10 CH11 CH12 CH1 CH2 CH5 CH6 CH5 CH6 CH7 CH8 CH13 CH14 CH15 CH16 CH3 CH4 CH7 CH8 VIDEO IN IN1 IN2 IN3 IN4 AUDIO IN LAN VGA HDMI AUDIO OUT RS485 USB DC 12 V LAN 4 Connect a monitor VIDEO IN IN1 IN2 IN3 IN4 AUDIO IN eSATA VGA AUDIO OUT HDMI USBView the Launcher Menu The Launcher menu appears on the bottom of the live screen. 1. In Live mode, right-click to display the context menu and select. 2. Move the cursor to the bottom and click a desired item in the 2013-01-01 01:10:25 2013-01-01 01:10:25 Launcher menu. 1 2 MM `` If no input is entered for 10 seconds, the menu will disappear. `` The Launcher menu can be accessed only by using the mouse. `` Screen mode may vary depending on the DVR supported channel.4. After filling in the information, Click . English Network Setting  Connection Mode 1. Click on Network and select. If there occur a problem with Connection Mode, check the connection as "Installing your system" on page 1. If you still have a problem, contact the nearest service center for more information. 2. Under Tab. Check is set to as default. SETTING UP SAMSUNG iPOLIS DDNS Since you will be accessing the DVR remotely, let's setup your Samsung iPolis account first using the PC. Go to Your PC 1. Open your browser and go to and click . 2. You first need to create an account. Click . 3. Follow-the account registration instructions on the website. 1 2 4. After completing the account registration, login to your account. JJ Write down your User ID and Password below. 1 ID 2 Password 5.Go back to DVR 1. From network tab, click on . English 2. Under DDNS Site, select . 3. Under Product ID, enter the product ID you created on the Samsung iPOLIS website. Under Quick Connect, select and click . JJ Write down the DDNS Host address:. 1 1 DDNS Host Address If the connection was not successful, your router may not be supporting UPNP. For more information on enabling UPNP on your router, please see User manual.REMOTE MONITORING From a Windows computer 1. Open Windows Internet Explorer and go to . com and click . 2. Login with the user ID and password you wrote down earlier. 3. Click < >. 4. You will be asked to install the active X plug-in. 5. Enter the user ID and password for the DVR. JJ If the screen to the bottom right does not appear, check if the DVR set is connected properly with a valid IP address. 6.USING A SMARTPHONE  For Android Phone SDR-3100 SDR-5102 www.samsungipolis.com/sdr-5102 00 4524 admin 2 Search for Samsung iPOLIS. 3 L aunch the iPOLIS mobile app add the DVR. Tap on the menu icon and tap . 4 R egister the DVR to the iPOLIS mobile. JJ Name : Create a name for the DVR you are adding Model : Select the DVR Host : If you are using Samsung iPOLIS DDNS, enter the DDNS Host Address you wrote down earlier. (Page 6, 7) It should be www.samsungipolis. For iPhone SAMSUNG TECHWIN C... Utilities Install 1 V isit App Store to Download the Samsung iPOLIS mobile app. 2 Search for Samsung iPOLIS. 4 Register the DVR to the iPOLIS mobile. 3 L aunch the iPOLIS mobile app add the DVR. At the Add Device pop-up, tap. MM `` For more information of each item, refer to "For Android Phone". SDR-5102 DVR www.samsungipolis.com/s... 80 4524 RECORDING AND PLAYBACK 1. Press the [MENU] button on the remote control.To change the record quality & resolution, select . System NTSC Possible FPS OFF, 1~30 English PAL Record Size CIF 352 x 240 2CIF 704 x 240 4CIF 704 x 480 WD1: 960 x 480 CIF 352 x 288 2CIF 704 x 288 4CIF 704 x 576 WD1: 960 x 576 OFF, 1~25 3. In Live mode, click in the right-click menu. Select in the menu.Page 2English 3EnglishRear2 Connect an BNC cameraVGA LANRS485IN1CH1 CH2 CH3 CH4 CH5 CH6 CH7 CH8CH9 CH10 CH11 CH12 CH13 CH14 CH15IN2IN3 IN4AUDIO INVIDEO INHDMI DC 12 VUSBeS ATAAUDIO OUTCH16VGA LANRS485IN1CH1 CH2 CH3 CH4CH5 CH6 CH7 CH8IN2IN3 IN4AUDIO INVIDEO INHDMI DC 12 VUSBeS ATAAUDIO OUTVGA LANRS485IN1CH1 CH2CH3 CH4IN2IN3 IN4AUDIO INVIDEO INHDMI DC 12 VUSBeS ATAAUDIO OUT4 Connect a monitor5 Connect the DC adaptors (DVR)3 Connect the DC adaptors (Camera) 6 Connect to a network routerPage 3ManualShelf © 2013-2025USA Ask the publishers to restore access to 500,000+ books. User Manuals, Guides and Specifications for your Samsung SDR-5102 DVR, Security System. Database contains 3 Samsung SDR-5102 Manuals (available for free online viewing or downloading in PDF): Operation & user's manual, Quick start manual . The Shop Samsung app Free standard shipping, exclusive offers and financing options.